

RS-918

HF SDR Transceiver

Features

- Spectrum Dynamic Waterfall Display
- Multiple Working Modes: Receive Mode, Transmit Mode, TUNE Mode, VFO Mode, SPLIT Mode
- DSP (Digital Signal Processing) Noise Reduction
- Automatic Notch Filter
- Humanized Interface Color Display
- Receive Fine Tuning Function, Changeable MIC Gain Value VCC Power Supply Voltage Indication Table
- Transmit Signal Strength Display Table
- Multifunctional Instrument: SWR Standing Wave Ratio Meter, AVD Audio Frequency Meter, ALC Signal Modulation Meter

Specifications

- Frequency Range:RX:1.8MHz-30MHz, TX:1.8MHz-30MHz
- Output Power: Maximum 15W
- Receiving Sensitivity:<-95dBm
- Operating Mode:SSB(J3E),CW,AM,FM,FREE-DV
- Dimensions:190mm*69mm*45mm
- Operating Voltage Range:DC 9-15V
- Maximum Current:3.5A
- Weight: 623g (Mounting Bracket Included)



HM-918
Hand Microphone



MB-918
Mounting Bracket



PL-918
DC Power Cable



SH-918
Side Handles